80 PLUS Verification and Testing Report


| TYPICAL EFFICIENCY (50% Load): | 94.43% |
|--------------------------------|--------|
| AVERAGE EFFICIENCY: | 93.22% |
| 80 PLUS COMPLIANT: | YES |



| Ecos ID# | SO-935.1 | | | |
|---------------|--------------------------|--|--|--|
| Manufacturer | Supermicro Computer Inc. | | | |
| Model Number | PWS-407P-1R | | | |
| Serial Number | N/A | | | |
| Year | 2015 | | | |
| Туре | 1U | | | |
| Test Date | 06/19/15 | | | |

| Rated Specifications | Value | Units |
|----------------------|---------|-------|
| Input Voltage | 100-240 | Volts |
| Input Current | 6.0-3.0 | Amps |
| Input Frequency | 50-60 | Hz |
| Rated Output Power | 400 | Watts |


Note: All measurements were taken with input voltage at 230 V nominal and 60 Hz.




Input AC Current Waveform (ITHD = 8.76%, 50% Load)

| I _{RMS} | PF | I _{THD} (%) | Load | Fraction Input External | | External | DC Terminal Voltage (V)/ DC Load Current (A) | | Output | |
|------------------|------|----------------------|------|-------------------------|-------|----------|--|-----------|--------|--------------|
| Α | | | (%) | of Load | Watts | Fan (W)* | 12V | 5Vsb | Watts | Efficiency % |
| 0.26 | 0.79 | 29.99 | 10% | Low | 48 | 1.31 | 12.27/3.21 | 5.05/0.29 | 41 | 85.64% |
| 0.43 | 0.91 | 20.42 | 20% | Light | 89 | 1.31 | 12.26/6.45 | 5.05/0.58 | 82 | 92.05% |
| 0.96 | 0.98 | 8.76 | 50% | Typical | 217 | 1.31 | 12.24/16.11 | 5.02/1.46 | 205 | 94.43% |
| 1.92 | 1.00 | 5.29 | 100% | Full | 439 | 1.90 | 12.25/32.23 | 4.98/2.92 | 409 | 93.17% |

^{*} Fan power is not included in the efficiency calculations







PLUG LOAD
These tests were conducted by a third party independent testing firm on behalf of the 80 PLUS® Program. 80 PLUS is a certification program to promote highly-efficient power supplies (greater than 80% efficiency in the active mode) in technology applications. http://www.80plus.org/

